

# RS-232 / RS-422 / RS-485 to ETHERNET CONVERTER

# DCEW-0131

## FEATURES


- Use HTTP, IE / Netscape browser for setting
- Set up login in password protection, firmware upgradeable
- Network protocols for ARP, ICMP, TCP, UDP, IP, DHCP client, HTTP
- Support 3 sockets for SIO, digital I/O and HTTP
- High stability, non-flammable case (PC), high safety



## SPECIFICATION


- ◆ LED Indication:
  - SYS: Red high bright round LED
  - LINK: Green high bright round LED
  - RX: Green high bright round LED
  - TX: Hred high bright round LED
- ◆ Baud Rate: Up to 115200 bps
- ◆ Serial Port:
  - RS-232 x 1
  - RS-422 x 1
  - RS-485 x 1
- ◆ Ethernet Port: 10M Base-T x 1
- ◆ Socket: 3 sockets
- ◆ CPU: 8051 microcontroller
- ◆ Flash Memory: 64 KB
- ◆ Memory: 32 KB
- ◆ Protocol Support: TCP/IP, ModBus/TCP
- ◆ System Configuration: Web configuration or Setup tools
- ◆ Operating Temperature: 0~55°C
- ◆ Operating Humidity: 20~95% RH (non-condensing)
- ◆ Storage Temperature: -10~70°C
- ◆ Storage Humidity: 20~95% RH (non-condensing)
- ◆ Terminal Resistance: 120Ω
- ◆ Installation: Surface mount, wall mount

## FRONT PANEL



- a. 10/100M Ethernet Port
- b. 24VDC Power
- c. System LED Indicator
- d. D-Sub RS232 Connector
- e. RS485/RS422 Connector

## DIMENSION



## WIRING CONNECTION

